



## Configuration of Eten P300 for Sunsurf Mobile

1. Click Start then go to Settings
2. On the Connections Tab, Select Connections
3. Under **My ISP**, Select **Add a new modem connection**

Enter a name for the Connection

M1 GPRS

Select a modem

Cellular Line GPRS

4. Enter the access point name

Access point name:

5. Enter the access point name

Access point name:

sunsurf

6. Enter 65XXXXXXXX (where the last 8 digits is your mobile number). Enter user123 as the Password Click **Advanced** to make sure **that "Use server-assigned IP address"** is checked under TCP/IP Tab. Make sure **"User server assigned addressees"** is checked under **Servers** Tab. Click **OK** and Finish and the then click OK again at the top right hand corner.
7. Make sure the phone is connected. i.e. Flight mode is off.
8. You can now launch your Pocket Internet Explorer.



## Configuration of Eten P300 for M1 MMS

1. Click **Start** then go to **Settings**
2. On the **Connections** Tab, Select **Connections**
3. Under **My Work Network**, Select **Add a new modem connection**

Enter a name for the Connection

M1 MMS

Select a modem

Cellular Line GPRS

4. Enter the access point name

Access point name:

5. Enter the access point name

Access point name:

miworld

6. Enter 65XXXXXXXX (where the last 8 digits is your mobile number). Enter user123 as the Password Click **Advanced** to make sure that **"Use server-assigned IP address"** is checked under TCP/IP Tab. Make sure **"User server assigned addressees"** is checked under **Servers** Tab. Click **OK** and Finish.

7. Next select the **Proxy Settings** Tab. Check "This network connects to the Internet". Also check "The network uses a proxy server to connect to the Internet"

This network connects to the Internet

The network uses a proxy server to connect to the Internet

8. Click the Advanced... button. Under WAP. Enter 172.16.1.23. For WAP Port, make sure it is defaulted at 9201.

WAP:

172.16.1.23

:

9201



9. Click **Start** then go to **Programs**
10. Click on the **Phone** icon folder then click on MMS Composer
11. At the bottom of MMS Composer, select **Tools** then **Options**
12. Then select Connect via: "**The Wap Network**"

**Connect Via:**

The Wap Network | v

13. On the Servers Tab, tap and hold on the screen to bring up the **New** (server) option
14. Key in **M1 MMS** as the name of the server. For Gateway key in **172.16.14.10** and for server address, key in **http://172.16.14.20:8002** . Click OK .

**Server Name:**

M1 MMS

**Gateway:**

172.16.14.10

**Server Address:**

http://172.16.14.20:8002

14. Click back to the Preferences Tab. Under Connect to Server, select M1 MMS as the server to connect.

**Connect to Server:**

M1 MMS